

Seltek International



✉
seltek@seltek.net

🌐
www.seltek.net



Beneli



Beneli 2.0



Beneli 4.0

MAIN FEATURE

workpiece travels into the heating chamber

SPECIFICATIONS

Operation Assembly

on table

Operation Method

one cylce at a time

Piece/s Per Cycle

1 piece

Cycle Time

variable time (1-100) seconds

Tube Size

up to 1 inch in diameter
up to 5 inches long

up to 1 inch in diameter
up to 4 inches long

up to 1 inch in diameter
up to 4 inches long

Operation Temperature

0°C to 600°C maximum

Electric Supply

120 VAC, 10 Amp, 3H, 50/60 Hz

BASIC FEATURES

Operation Mode

✓

✓

✓

Capable Of Processing Splices

✓

✓

✓

Controlled By

PLC

HMI

HMI

Capable Of Processing Small Battery And Ring Terminals

✓

✓

✓

SMART FEATURES

Touch Screen

X

✓

✓

Parameter Selection Mode

manual

manual

manual and by memory

Code Reader

X

X

✓

Ready For 4.0 Manufacturing

X

X

✓

Network Communication

X

X

✓

Password Protected

X

✓

✓

Seltek International



seltek@seltek.net



www.seltek.net



Mini Toaster 4.0

Super Toaster 2.0

Super Toaster 4.0

Super Toaster Doble 4.0

MAIN FEATURE

the heat chamber travels to the workpiece and the pieces does not move

SPECIFICATIONS

Operation Assembly	on table	integrated table	integrated table	integrated table
Operation Method	(controlled process) once cycle at a time			
Piece/s Per Cycle	1-3	6-18	6-18	6-18
Cycle Time	variable time (1-100) seconds			
Tube Size	up to 1 inch in diameter up to 5 inches long	up to 1.5 inch in diameter up to 3 inches long	up to 1.5 inch in diameter up to 3 inches long	up to 1.5 inch in diameter up to 3 inches long
Operation Temperature	0°C to 600°C maximum			
Electric Supply	120 VAC, 12 Amp, 3H, 50/60 Hz	240 VAC, 4 H, 25 AMP, 50-60 HZ	240 VAC, 4 H, 25 AMP, 50-60 HZ	240 VAC, 4 H, 25 AMP, 50-60 HZ
BASIC FEATURES				
Operation Mode	semiautomatic	semiautomatic	semiautomatic	semiautomatic
Capable Of Processing Splices	✓	✗	✗	✗
Capable Of Processing Small Battery Terminals And Ring Terminals	✓	✓	✓	✓
SMART FEATURES				
Parameter Selection Mode	manual and by memory	manual	manual and by memory	manual and by memory
Bar Code And QR Reader	✓	✗	✓	✓
Ready For 4.0 Manufacturing	✓	✓	✓	✓
Network Communication	✓	✗	✓	✓
Password Protected	✓	✓	✓	✓